


LUCKY EVO B

100285.02H + 100250.99

LUCKY EVO B:HF D/I 56W L1406 4KNE PUSH + LUCKY EVO B/C: DIFF. OPALE PER L1406



novalux
ITALIAN LIGHTING DESIGN SINCE 1948



Features

Use: Indoor
Type of installation: SUSPENDED
Emission: DIRECT/INDIRECT
Optics: OPAL
Colour: BLACK
Dimming: PUSH
Emergency: NO
L: 1406mm
A: 52mm
H: 91mm
Made in: ITALY
Warranty: 5 years
Weight: 5kg

Tech data

Luminaire input power: 62.9W
Luminaire luminous flux: 5491lm
Indirect luminous flux: 2968lm
IP: 40
Insulation class: I
Supply voltage: 220-240V 50/60Hz
SELV: Si

Source

Light source: LED
Source power: 56W
Source luminous flux: 8737lm
Colour temperature: 4000K
CRI: >80
Colour tolerance: 3 Step MacAdam
LED lifespan: 50000h L80 B20

Compliance

CEI EN 60598-1:2015 + A11:2009. IEC 60598-2:2015 2-1

Standards

Photobiological risk: RISK GROUP 0 Certified fixture in EXEMPT GROUP, in accordance with CEI EN 62471:2010-01, IEC TR 62778:2014.
CAM edilizia: The product complies with the requirements for public buildings, ministerial decree of 23rd June 2022 n.256.

[LUCKY EVO B: View more product info](#)



Novalux S.r.l. via Marzabotto, 2 40050 Funo di Argelato (BO) Italy
Tel: +39 051 860558 · Fax +39 051 6647859 · Mail: info@novalux.it · VAT number 00536541204 · novalux.com
Company subject to the management and coordination by SLV GmbH

This technical data sheet is owned by Novalux S.r.l., all rights reserved. Novalux S.r.l. reserves the right to make changes without prior notice.
Last update: 6/8/2025, 13:07:10

LUCKY EVO B

100285.02H + 100250.99

LUCKY EVO B:HF D/I 56W L1406 4KNE PUSH + LUCKY EVO B/C: DIFF. OPALE PER L1406



novalux
ITALIAN LIGHTING DESIGN SINCE 1948





Features

Use: Indoor
Optics: OPAL
Emergency: NO
L: 1406mm
A: 48mm
H: 10mm
Made in: ITALY
Warranty: 5 years
Weight: 0.2kg

Tech data

IP: 40



Novalux S.r.l. via Marzabotto, 2 40050 Funo di Argelato (BO) Italy
Tel: +39 051 860558 · Fax +39 051 6647859 · Mail: info@novalux.it · VAT number 00536541204 · novalux.com
Company subject to the management and coordination by SLV GmbH

This technical data sheet is owned by Novalux S.r.l., all rights reserved. Novalux S.r.l. reserves the right to make changes without prior notice.
Last update: 6/8/2025, 13:07:10






LUCKY EVO B

100285.02H + 100250.99

LUCKY EVO B:HF D/I 56W L1406 4KNE PUSH + LUCKY EVO B/C: DIFF. OPALE PER L1406

novalux
ITALIAN LIGHTING DESIGN SINCE 1948

COMPLETION ACCESSORIES

	LUCKY EVO B: MODULO CIECO L=1125 NERO	100261.02
	LUCKY EVO B: MODULO CIECO L=1406 NERO	100262.02
	LUCKY EVO B: MODULO CIECO L=1687 NERO	100263.02
	LUCKY EVO B: MODULO CIECO ANG. L=592 NE	100264.02
	LUCKY EVO B: COPPIA TESTATE CHIUSURA NER	100247.02
	LUCKY EVO B: KIT GIUNZIONE MODULI	100248.01

MOUNTING ACCESSORIES

	KIT ALIMENTAZIONE L1200 3P NE	108919.02
	KIT ALIMENTAZIONE L3000 3P NE	108920.02
	KIT ALIMENTAZIONE L1200 5P NE	108921.02
	KIT ALIMENTAZIONE L3000 5P NE	108922.02



Novalux S.r.l. via Marzabotto, 2 40050 Funo di Argelato (BO) Italy
Tel: +39 051 860558 · Fax +39 051 6647859 · Mail: info@novalux.it · VAT number 00536541204 · novalux.com
Company subject to the management and coordination by SLV GmbH

This technical data sheet is owned by Novalux S.r.l., all rights reserved. Novalux S.r.l. reserves the right to make changes without prior notice.
Last update: 6/8/2025, 13:07:10

LUCKY EVO B

100285.02H + 100250.99

LUCKY EVO B:HF D/I 56W L1406 4KNE PUSH + LUCKY EVO B/C: DIFF. OPALE PER L1406

novalux
ITALIAN LIGHTING DESIGN SINCE 1948



LUCKY EVO B: KIT COPPIA CAVI SOSP. 5 M

1002B5.99



Novalux S.r.l. via Marzabotto, 2 40050 Fano di Argelato (BO) Italy
Tel: +39 051 860558 · Fax +39 051 6647859 · Mail: info@novalux.it · VAT number 00536541204 · novalux.com
Company subject to the management and coordination by SLV GmbH

This technical data sheet is owned by Novalux S.r.l., all rights reserved. Novalux S.r.l. reserves the right to make changes without prior notice.
Last update: 6/8/2025, 13:07:10