
LUCKY EVO B

1002D6.01H + 1002A3.99

LUCKY EVO B: HF D/I 120W L2811 3KBI PUSH + LUCKY EVO B: DIFF. OPALE PER L2811





Features

Use: Indoor
Type of installation: SUSPENDED
Emission: DIRECT/INDIRECT
Optics: OPAL
Colour: WHITE
Dimming: PUSH
Emergency: NO
L: 2811mm
A: 52mm
H: 91mm
Made in: ITALY
Warranty: 5 years
Weight: 9.4kg

Tech data

Luminaire input power: 132.7W
Luminaire luminouse flux: 11242lm
Indirect luminous flux: 6367lm
IP: 40
Insulation class: I
Supply voltage: 220-240V 50/60Hz
SELV: Sì

Source

Light source: LED
Source power: 120W
Source luminous flux: 17808lm
Colour temperature: 3000K
CRI: >80
Colour tolerance: 3 Step MacAdam
LED lifespan: 50000h L80 B20

Compliance

CEI EN 60598-1:2015 + A11:2009. IEC 60598-2:2015 2-1

Standards

Photobiological risk: RISK GROUP 0Certified fixture in EXEMPT GROUP, in accordance with CEI EN 62471:2010-01, IEC TR 62778:2014.
CAM edilizia: The product complies with the requirements for public buildings, ministerial decree of 23rd June 2022 n.256.

LUCKY EVO B: View more product info

Novalux S.r.l. via Marzabotto, 2 40050 Funo di Argelato (BO) Italy
Tel: +39 051 860558 · Fax +39 051 6647859 · Mail: info@novalux.it · VAT number 00536541204 · novalux.com
Company subject to the management and coordination by SLV Gmbh

This technical data sheet is owned by Novalux S.r.l., all rights reserved. Novalux S.r.l. reserves the right to make changes without prior notice.
Last update: 9/6/2026, 17:22:07

LUCKY EVO B

1002D6.01H + 1002A3.99

LUCKY EVO B: HF D/I 120W L2811 3KBI PUSH + LUCKY EVO B: DIFF. OPALE PER L2811




Features

Use: Indoor
Optics: OPAL
Emergency: NO
L: 2811mm
A: 48mm
H: 10mm
Made in: ITALY
Warranty: 5 years
Weight: 0.5kg

Tech data

IP: 40



Novalux S.r.l. via Marzabotto, 2 40050 Funo di Argelato (BO) Italy
Tel: +39 051 860558 · Fax +39 051 6647859 · Mail: info@novalux.it · VAT number 00536541204 · novalux.com
Company subject to the management and coordination by SLV Gmbh



This technical data sheet is owned by Novalux S.r.l., all rights reserved. Novalux S.r.l. reserves the right to make changes without prior notice.
Last update: 9/6/2026, 17:22:07

LUCKY EVO B

1002D6.01H + 1002A3.99

LUCKY EVO B: HF D/I 120W L2811 3KBI PUSH + LUCKY EVO B: DIFF. OPALE PER L2811

COMPLETION ACCESSORIES

	LUCKY EVO B: MODULO CIECO L=1125 BIANCO	**100261.01**
	LUCKY EVO B: MODULO CIECO L=1406 BIANCO	**100262.01**
	LUCKY EVO B: MODULO CIECO L=1687 BIANCO	**100263.01**
	LUCKY EVO B: MODULO CIECO ANG. L=592 BI	**100264.01**
	LUCKY EVO B: COPPIA TESTATE CHIUSURA BIA	**100247.01**
	LUCKY EVO B: KIT GIUNZIONE MODULI	**100248.01**

MOUNTING ACCESSORIES

	KIT ALIMENTAZIONE L1200 3P BIA	**108919.01**
	KIT ALIMENTAZIONE L3000 3P BIA	**108920.01**
	KIT ALIMENTAZIONE L1200 5P BIA	**108921.01**
	KIT ALIMENTAZIONE L3000 5P BIA	**108922.01**

Novalux S.r.l. via Marzabotto, 2 40050 Funo di Argelato (BO) Italy
Tel: +39 051 860558 · Fax +39 051 6647859 · Mail: info@novalux.it · VAT number 00536541204 · novalux.com
Company subject to the management and coordination by SLV Gmbh

This technical data sheet is owned by Novalux S.r.l., all rights reserved. Novalux S.r.l. reserves the right to make changes without prior notice.
Last update: 9/6/2026, 17:22:07

LUCKY EVO B

1002D6.01H + 1002A3.99

LUCKY EVO B: HF D/I 120W L2811 3KBI PUSH + LUCKY EVO B: DIFF. OPALE PER L2811



LUCKY EVO B: KIT COPPIA CAVI SOSP. 5 M **1002B5.99**

Novalux S.r.l. via Marzabotto, 2 40050 Funo di Argelato (BO) Italy
Tel: +39 051 860558 · Fax +39 051 6647859 · Mail: info@novalux.it · VAT number 00536541204 · novalux.com
Company subject to the management and coordination by SLV Gmbh

This technical data sheet is owned by Novalux S.r.l., all rights reserved. Novalux S.r.l. reserves the right to make changes without prior notice.
Last update: 9/6/2026, 17:22:07