



LUCKY EVO

100520.01 + 100575.99

LUCKY EVO: LED 38W EM.4K BIA L=1687 + LUCKY EVO: DIFF.TRAS.+MICROS. PER L1687



novalux
ITALIAN LIGHTING DESIGN SINCE 1948



Features

Use: Indoor

Type of installation: WALL, RECESSED INTO PLASTERBOARD, SUSPENDED, CEILING MOUNTED, TRACK

Emission: DIRECT

Optics: MICRO-STRUCTURED

Colour: WHITE

Dimming: ON/OFF

Emergency: Autonomy 1h/Recharge time 12h

L: 1687mm

A: 52mm

H: 80mm

Made in: ITALY

Warranty: 5 years except battery

Weight: 5kg

Tech data

Luminaire input power: 40.5W

Luminaire luminous flux: 3005lm

Luminous flux in emergency: 9%

IP: 40

Insulation class: I

Supply voltage: 220-240V 50/60Hz

UGR: <19

SELV: Si

Source

Light source: LED

Source power: 38W

Source luminous flux: 5829lm

Colour temperature: 4000K

CRI: >80

Colour tolerance: 3 Step MacAdam

LED lifespan: 50000h L80 B20

Compliance

CEI EN 60598-1:2015 + A11:2009. IEC 60598-2:2015 2-1, 2-2, 2-22

Standards

Photobiological risk: RISK GROUP 0 Certified fixture in EXEMPT GROUP, in accordance with CEI EN 62471:2010-01, IEC TR 62778:2014.

CAM edilizia: The product complies with the requirements for public buildings, ministerial decree of 23rd June 2022 n.256.

[LUCKY EVO: View more product info](#)



Novalux S.r.l. via Marzabotto, 2 40050 Funo di Argelato (BO) Italy
Tel: +39 051 860558 · Fax +39 051 6647859 · Mail: info@novalux.it · VAT number 00536541204 · novalux.com
Company subject to the management and coordination by SLV GmbH

This technical data sheet is owned by Novalux S.r.l., all rights reserved. Novalux S.r.l. reserves the right to make changes without prior notice.
Last update: 6/8/2025, 13:11:00

LUCKY EVO

100520.01 + 100575.99

LUCKY EVO: LED 38W EM.4K BIA L=1687 + LUCKY EVO: DIFF.TRAS.+MICROS. PER L1687



novalux
ITALIAN LIGHTING DESIGN SINCE 1948





Features

Use: Indoor
Optics: MICRO-STRUCTURED
L: 1687mm
A: 48mm
H: 10mm
Made in: ITALY
Warranty: 5 years
Weight: 0.3kg

Tech data

IP: 40
UGR: <19



Novalux S.r.l. via Marzabotto, 2 40050 Funo di Argelato (BO) Italy
Tel: +39 051 860558 · Fax +39 051 6647859 · Mail: info@novalux.it · VAT number 00536541204 · novalux.com
Company subject to the management and coordination by SLV GmbH

This technical data sheet is owned by Novalux S.r.l., all rights reserved. Novalux S.r.l. reserves the right to make changes without prior notice.
Last update: 6/8/2025, 13:11:00

LUCKY EVO

100520.01 + 100575.99

LUCKY EVO: LED 38W EM.4K BIA L=1687 + LUCKY EVO: DIFF.TRAS.+MICROS. PER L1687

novalux
ITALIAN LIGHTING DESIGN SINCE 1948

COMPLETION ACCESSORIES



LUCKY EVO: TESTATE COPPIA BIA

18750.01



LUCKY EVO: KIT DI GIUNZ. RETTILINEO

18751.99

MOUNTING ACCESSORIES



HERO: SOSP.L3000 1PZ TESTA W.G.BASSO

108685.99



LUCKY EVO: SOSP.L3000 1PZ. UNIONE

18757.99



LUCKY EVO: SPESS. CARTONG. 10MM 4PZ.

18753.99



KIT ALIMENTAZIONE L3000 3P NE

108920.02



LUCKY EVO: KIT INCASSO LED (2X)

18752.99



KIT ALIMENTAZIONE L1200 3P NE

108919.02



LUCKY EVO: STAFFA PARETE "L" BIA

1005A2.01



Novalux S.r.l. via Marzabotto, 2 40050 Funo di Argelato (BO) Italy
Tel: +39 051 860558 · Fax +39 051 6647859 · Mail: info@novalux.it · VAT number 00536541204 · novalux.com
Company subject to the management and coordination by SLV GmbH

This technical data sheet is owned by Novalux S.r.l., all rights reserved. Novalux S.r.l. reserves the right to make changes without prior notice.
Last update: 6/8/2025, 13:11:00